

## Requirements:


Note: This is only a MainSystem Software update via USB drive

- USB stick with at least 2 GB memory.
- A Windows based PC or notebook to prepare the USB.

Note: The USB stick must be formatted to FAT32 before use (right-click on the USB drive in the Win Explorer → choose "Format" → select FAT 32 → start).

## Installation of MainSystem Software Update via USB drive:

1. Download the software update package „Z-E6150\_FEU\_SW\_v2.3.exe”.
2. The software package is a self-unzipping executable. Start extraction with a double-click and select your USB stick as target for the uncompressed files.
3. You obtain a folder called „BIN” and two update files “DownLoad.bin”, “updW\_mcu32.img” in the root directory of the USB stick.



4. Connect the USB stick to your powered on naviceiver.
5. Enter the naviceiver setup. Tap on “Setup” → “System” → “Software Update” → [OK].
6. The naviceiver show the update dialog pop up. Tap on the [OK] button to start the update process.
7. Your system will restart and will be updated in a step-by-step process. The complete update procedure takes approx. 1~2 minutes. A status bar shows the update progress.
8. Please remove the USB stick and restart your ZENEC naviceiver by tap to [OK] button, if the update process has completed successfully.
9. Please do a versions check.

## Version checking:

After completion of the software update, version checking is crucial to validate full success. If the installed software version differs with listed versions below, a full re-installation of the entire software update is required.

### Review of device software version:

To check the Main Software Version, enter the naviceiver setup. Tap on “Setup” → “System” → tap to → “Software Version Info”

Version:	ZENEC V2.3
APP:	M1421-2201-171031QA
OS:	T8_2201_170417_01
MCU:	ST32_01_20171030_01
DVP:	01171606 Servo 83140060
BT:	M70B44B47A36A35H23

## Notes:

- Do not operate or turn off while device is performing a software update.

**Improvements + Bugfixes:****MainSystem General**

---

- Improved system stability and performance
- Improved audio-mixer logic in combination with active route navigation
- Improved navigation auto-boot start up

**Tuner**

---

- Improved FM Tuner auto-scan logic (AF)

**Bluetooth**

---

- Bugfix for Bluetooth Contact list (phone book), sometimes can't open after an active call

**Camera**

---

- Bugfix for mute function during active camera image